

DUAL FX

PARAM 1

Adjust the first parameter of the effect

SAVE

Push and hold the SAVE button for 2" to save the parameter and dry/wet settings with the effect. To recall parameter and dry/wet settings, push the SAVE button promptly. All three effect select LEDs will blink once to confirm setting recall. Now, if you turn the parameter knobs to alter the settings, the LEDs will flash once, when the saved position of the potentiometer is reached. Only then parameter changes will take effect.

PARAM 2

Adjust the second parameter of the effect

LEDs

These are the effect indicator LEDs. They indicate one of 8 selected effects in binary code. Please, refer to the Effect table below!

DRY/WET

This is dry/wet control potentiometer

SELECT

This is effect select button. Push it promptly to navigate thru effects. To assign CV input to control one of the parameters or dry/wet setting, push and hold the button for 2". The first effect indicator LED will start to flash, indicating that the CV is assigned to the first parameter. Push the button repeatedly to assign the CV input to the 2nd effect or to dry/wet control. Push the SAVE button to confirm

CV IN

This is the assignable CV input

IN 1

This is the audio input. The effects are designed to add stereo spread to the mono input signal

OUT L, OUT R

These are left and right outputs. We highly recommend to use the module with the stereo mixer



FX	DRY/WET	PARAM1	PARAM 2
MONO DELAY	DRY/WET	TIME	FEEDBACK
STEREO DELAY	DRY/WET	TIME	FEEDBACK
HI PASS DELAY	DRY/WET	TIME	HI PASS FILTER
BIG REVERB	DRY/WET	SIZE	STONE
SATURATED REVERB	DRY/WET	SIZE	STONE
STALKER REVERB	DRY/WET	STONE	FEEDBACK
RIPPER	DRIVE	CRUSH	DELAY TIME
DUAL PITCH SHIFTER	DRY/WET	SHIFT 1	SHIFT 2



SAFETY INSTRUCTIONS

Please follow the instructions for use of the Erica Synths module below, 'cause only this will guarantee proper operation of the module and ensure warranty from Erica Synths.



Water is lethal for most of the electric devices, unless they are made waterproof. This Erica Synths module is NOT intended for use in a humid or wet environment. No liquids or other conducting substances must get into the module. Should this happen, the module should be disconnected from mains power immediately, dried, examined and cleaned by a qualified technician.



Do not expose the module to temperatures above +50° C or below -20° C. If you have transported module in extreme low temperatures, leave it in room temperature for an hour before plugging it in.



Transport the instrument carefully, never let it drop or fall over. Warranty does not apply to modules with visual damages.



The module has to be shipped in the original packaging only. Any module shipped to us for return, exchange and/or warranty repair has to be in its original packaging. All other deliveries will be rejected and returned to you. Make sure you keep the original packaging and technical documentation.



This device complies to the EU guidelines and is manufactured RoHS conforming without use of lead, mercury, cadmium and chrome. Nevertheless, this device is special waste and disposal in household waste is not recommended.

You will find Erica Synths terms of warranty at www.ericasynths.lv

Items for return, exchange and/or warranty repair have to be sent to:

Erica Synths
Andrejostas Str. 43
Riga
Latvia
LV-1045

User manual by Girts Ozolins@Erica Synths.

Design by Ineta Briede@Carre Branding.

Copying, distribution or any commercial use in any way is prohibited and needs the written permission by Erica Synths.

Specifications are subject to change without notice.

In case of any questions, feel free to contact us through www.ericasynths.lv or via e-mail info@ericasynths.lv

THANK YOU FOR PURCHASING ERICA SYNTHS DRUM MODULE!

Erica Drum Series modules include high-end, unique functionality and superior quality modules, which allow you to design extensive, feature rich modular system for sound design and live performances. Enjoy!

To add some space to your compositions and nuances in sound design (a proper techno bass drum needs some reverb) Erica Synths Dual FX module brings you two identical sections of 8 custom effects with two adjustable and CV controllable parameters. Furthermore, CV input can be assigned to both parameters and dry/wet setting, as well as parameters settings can be saved with an effect and recalled instantly during the performance.

FEATURES

Two identical FX sections
8 great sounding custom stereo effects
2 adjustable parameters per effect
Assignable CV control
Dry/Wet control
Parameter setting memory
Stereo output

SPECS

Audio output level	-5...+5V
CV level (full span)	-5V - +5V
Power consumption	118mA @ +12V, 61mA @ -12V
Module width	10HP
Module depth	45mm