

Domino₃

acoustic
solutions
advanced level



What was supposed to be an update turned into a different class ... Domino 3. Now really stereo, with two twin cone speakers and high performance poweramps. Two independent effect units, with 16 presets each, separately address pairs of the four equally equipped channels (1, 2 and 3, 4).

A little software tool (Windows) connects your laptop with the amp to modify effect parameters and create and save your own effects.

- 2 x 100 watts, dynamic control
- 2 x 8" twin cone stereo speaker system.
- Quad-channel acoustic system
- 32 bit AER digital effect processor with 16 presets.
- PC Software for managing individual effect presets
- 16,00 kg (35.50 lbs)

Inputs

channel 1 – 4 combined XLR/6.3 mm (1/4") input jack socket switchable for instruments, line-level or phantom powered sources (e.g. microphones).

Power

equalizer three band tone controls for each channel
colour 'mid-cut-treble-boost'-filter
effect 32 bit AER digital effect processor with 16 presets (can be modified via USB and PC Software).

Power

power amp 2 x 100 W / 4 ohms, dynamic control
analog signal processing subsonic filter, low distortion RMS limiter

Speaker System

2 x 8" twin cone speaker system

Features

switchable phantom power, ground lift, rec out, aux in, return, send, headphones, tuner, footswitch (internal/external effect on/off), adjustable DI-out

Accessories

softcover

Specifications

cabinet 15 mm (0.59") finnish birch plywood
finish waterbased acrylic, black spatter finish
dimensions 365 mm x 420 mm x 295 mm (14.37" x 16.53" x 11.69"), HxWxD
weight 16,00 kg (35.50 lbs)

Can be combined with

AS 281, AG 8

